

## TABLE 4 - Testing and Inspection Intervals for Electrical Equipment

(CAUTION: This page must be read in conjunction with AS/NZS 3760:2010 as a whole, and particularly clause 2.1)

Type of environment and/or equipment (a)	Interval between inspection and tests				
	Equipment including Class I equipment, Class II equipment, cord sets, cord extension sets and EPODs (b)	Residual current devices (RCDs)			
		Push-button test – by user		Operating time and push-button test	
		Portable (c)	Fixed (d)	Portable (e)	Fixed (f)
1 Factories, workshops, places of work or repair, manufacturing, assembly, maintenance or fabrication	6 months	Daily, or before every use, whichever is the longer	6 months	12 months	12 months
2 Environment where the equipment or <b>supply flexible cord</b> is subject to flexing in normal use OR is open to abuse OR is in a <b>hostile environment</b>	12 months	3 months	6 months	12 months	12 months
3 Environment where the equipment or <b>supply cord</b> is NOT subject to flexing in normal use and is <b>NOT</b> open to abuse and is <b>NOT</b> in a <b>hostile environment</b>	5 years	3 months	6 months	2 years	5 years
4 <b>Residential type areas</b> of: hotels, residential institutions, motels, boarding houses, halls, hostels accommodation houses, and the like	2 years	6 months	6 months	2 years	2 years
5 Equipment used for <b>commercial cleaning</b>	6 months	Daily, or before every use, whichever is the longer	N/A	6 months	N/A
6 <b>Hire equipment:</b>  Inspection  Test and tag	Prior to <b>hire</b>	Including push-button test by <b>hirer</b> prior to <b>hire</b>		N/A	N/A
	3 months	N/A		3 months	12 months
7 Repaired, serviced and second-hand equipment	After repair or service which could affect electrical safety, or on reintroduction to service, refer to AS/NZS 5762				